

```

/* Ventilator Arduino Sketch Revision 2
 * Dan Folmer - Northstar Load Cell and Scale
 * 4-3-2020
 *
 * The sketch is designed to control solenoid flow valves to create
 * a medical ventilator to assist a patient with breathing.
 *
 * The design criteria of the ventilator are:
 * 1. Provide pressure to facilitate inhalation.
 * 2. Built from components that are easily sourced and within
 * the capability of fabricators to build themselves.
 * 3. Expandable so that one machine can care for multiple
 * patients.
 */
int solInhaleHighPressPin = 5; // Pin signal controls the solenoid to pressurize the
mask.
int solExhalePin = 4; // Pin signal controls the solenoid to open the mask to allow
air out or seal it shut.
int delayTime = 0; // The breath cycle rate. Changed by the trim pot input.
int trimPotPin = A0; // Pin signal of the trim pot.
int trimPotPinValue = 0;

void setup() {
  // Declare the digital pins as OUTPUT type.
  pinMode(solInhaleHighPressPin, OUTPUT);
  pinMode(solExhalePin, OUTPUT);
}

void loop() {
  // Cycle the solenoid pin outputs to control airflow in
  // and out of the mask.
  digitalWrite(solInhaleHighPressPin, HIGH);
  digitalWrite(solExhalePin, LOW);
  delay(delayTime);
  digitalWrite(solInhaleHighPressPin, LOW);
  digitalWrite(solExhalePin, HIGH);
  delay(delayTime);

  // Convert the trim pot signal from the default analog values to milliseconds.
  trimPotPinValue = analogRead(trimPotPin);
  delayTime = map(trimPotPinValue, 0, 1023, 1000, 5000);
}

```